

The exact relation between the displacement current and the conduction current: Comment on a paper by Griffiths and Heald

José A. Heras*

*Departamento de Ciencias Básicas,
Universidad Autónoma Metropolitana, Unidad Azcapotzalco,
Av. San Pablo No. 180, Col. Reynosa, 02200,
México D. F. México and Departamento de Física y Matemáticas,
Universidad Iberoamericana, Prolongación Paseo
de la Reforma 880, México D. F. 01210, México*

Abstract

I introduce the exact relation between the displacement current $\epsilon_0 \partial \mathbf{E} / \partial t$ and the ordinary current $\mathbf{J}$. I show that $\epsilon_0 \partial \mathbf{E} / \partial t$ contains a local term determined by the present values of $\mathbf{J}$ plus a non-local term determined by the retarded values of $\mathbf{J}$. The non-local term implements quantitatively the suggestion made by Griffiths and Heald that the displacement current at a point is a surrogate for ordinary currents at other locations.

Griffiths and Heald have posed and answered the following question (their “recurring question (3)”):¹ “What relationship exists between the two sources in the Ampere-Maxwell law:

$$\nabla \times \mathbf{B} = \mu_0 \mathbf{J} + \mu_0 \epsilon_0 \frac{\partial \mathbf{E}}{\partial t}, \quad (1)$$

for instance, can one be derived from the other?” Their answer was the following:¹ “None. The two currents are independent and both are needed, in general. $\mathbf{J}$ represents the ordinary current at a point where the curl [of $\mathbf{B}$] is evaluated, while the “displacement current” $\epsilon_0 \partial \mathbf{E} / \partial t$ is a surrogate for ordinary currents at other locations.” The assumed lack of a specific relation between $\epsilon_0 \partial \mathbf{E} / \partial t$ and $\mathbf{J}$ led to the claim that the Biot-Savart law extended to include the displacement current:

$$\mathbf{B} = \frac{\mu_0}{4\pi} \int d^3x' \frac{(\mathbf{J} + \epsilon_0 \partial \mathbf{E} / \partial t) \times \hat{\mathbf{R}}}{R^2}, \quad (2)$$

“... is not useful because it is self-referential: To calculate $\mathbf{B}$ at a point, one must know $\mathbf{E}$ *everywhere* – but you can’t determine $\mathbf{E}$ unless you already know $\mathbf{B}$ (everywhere), because of Faraday induction [$\nabla \times \mathbf{E} = -\partial \mathbf{B} / \partial t$].” In Eq. (2) the integration is over all space and $\hat{\mathbf{R}} = \mathbf{R} / R = (\mathbf{x} - \mathbf{x}') / |\mathbf{x} - \mathbf{x}'|$.

In this comment I derive the exact relation between the displacement current $\epsilon_0 \partial \mathbf{E} / \partial t$ and the current $\mathbf{J}$. The existence of this relation allows us to answer in the affirmative the question posed and answered negatively by Griffiths and Heald.¹

Let me first introduce this relation which we will derive in the following:

$$\epsilon_0 \frac{\partial \mathbf{E}}{\partial t} = -\frac{\mathbf{J}}{3} + \frac{1}{4\pi} \int d^3x' \left(\frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\mathbf{J}]) - [\mathbf{J}]}{R^3} + \frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{J} / \partial t]) - [\partial \mathbf{J} / \partial t]}{R^2 c} + \frac{\hat{\mathbf{R}} \times (\hat{\mathbf{R}} \times [\partial^2 \mathbf{J} / \partial t^2])}{R c^2} \right), \quad (3)$$

where the square brackets [] indicate that the enclosed quantity is to be evaluated at the retarded time $t' = t - R/c$. Equation (3) provides the exact relation between the currents $\epsilon_0 \partial \mathbf{E} / \partial t$ and $\mathbf{J}$ and implies that the two currents are not independent. The first term represents a local part which exists in the region where $\mathbf{J}$ is defined and depends on the present values of $\mathbf{J}$. The second term is a non-local part which extends over all space and depends on the retarded values of $\mathbf{J}$. In short, the local contribution to $\epsilon_0 \partial \mathbf{E} / \partial t$ is instantaneously produced by $\mathbf{J}$, and the non-local contribution to $\epsilon_0 \partial \mathbf{E} / \partial t$ is causally produced by $\mathbf{J}$. It follows that the displacement current is produced by the present and retarded values of the ordinary current $\mathbf{J}$. The non-local part of $\epsilon_0 \partial \mathbf{E} / \partial t$ shows explicitly

how the displacement current at a point represents the contribution from ordinary currents elsewhere. Equation (3) implements quantitatively the suggestion made by Griffiths and Heald that:¹ “the displacement current at a point is a surrogate for ordinary currents at other locations.” These authors also claimed that Eq. (2) is self-referential. However, the substitution of Eq. (3) into Eq. (2) removes the self-referential aspect of Eq. (2). To calculate $\mathbf{B}$ by means of Eq. (2) we really need to know $\epsilon_0 \partial \mathbf{E} / \partial t$ and not necessarily $\mathbf{E}$, and we can calculate $\epsilon_0 \partial \mathbf{E} / \partial t$ from $\mathbf{J}$ using Eq. (3) with no explicit reference to $\mathbf{B}$.²

To obtain Eq. (3) we first consider the generalized Biot-Savart law:³

$$\mathbf{B} = \frac{\mu_0}{4\pi} \int d^3x' \left(\frac{[\mathbf{J}] \times \hat{\mathbf{R}}}{R^2} + \frac{[\partial \mathbf{J} / \partial t] \times \hat{\mathbf{R}}}{Rc} \right). \quad (4)$$

We next take the curl of Eq. (4)

$$\nabla \times \mathbf{B} = \frac{\mu_0}{4\pi} \int d^3x' \left(\nabla \times \left\{ \frac{[\mathbf{J}] \times \hat{\mathbf{R}}}{R^2} \right\} + \nabla \times \left\{ \frac{[\partial \mathbf{J} / \partial t] \times \hat{\mathbf{R}}}{Rc} \right\} \right). \quad (5)$$

The following identities are demonstrated in Appendix A:

$$\nabla \times \left\{ \frac{[\mathbf{J}] \times \hat{\mathbf{R}}}{R^2} \right\} = \frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\mathbf{J}]) - [\mathbf{J}]}{R^3} + \frac{\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{J} / \partial t]) - [\partial \mathbf{J} / \partial t]}{R^2 c} + \frac{8\pi}{3} [\mathbf{J}] \delta(\mathbf{x} - \mathbf{x}'), \quad (6)$$

$$\nabla \times \left\{ \frac{[\partial \mathbf{J} / \partial t] \times \hat{\mathbf{R}}}{Rc} \right\} = \frac{2\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{J} / \partial t])}{R^2 c} + \frac{\hat{\mathbf{R}} \times (\hat{\mathbf{R}} \times [\partial^2 \mathbf{J} / \partial t^2])}{Rc^2}, \quad (7)$$

where $\delta(\mathbf{x} - \mathbf{x}')$ is the Dirac-delta function. If we insert Eq. (6) [with its last term written as $4\pi[\mathbf{J}]\delta(\mathbf{x} - \mathbf{x}') - (4\pi/3)[\mathbf{J}]\delta(\mathbf{x} - \mathbf{x}')$] and Eq. (7) into Eq. (5), and integrate the Dirac-delta terms, we obtain

$$\begin{aligned} \nabla \times \mathbf{B} = \mu_0 \mathbf{J} + \mu_0 \left\{ -\frac{\mathbf{J}}{3} + \frac{1}{4\pi} \int d^3x' \left(\frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\mathbf{J}]) - [\mathbf{J}]}{R^3} + \frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{J} / \partial t]) - [\partial \mathbf{J} / \partial t]}{R^2 c} \right. \right. \\ \left. \left. + \frac{\hat{\mathbf{R}} \times (\hat{\mathbf{R}} \times [\partial^2 \mathbf{J} / \partial t^2])}{Rc^2} \right) \right\}. \end{aligned} \quad (8)$$

The term within the parentheses $\{ \}$ is identified as the term $\epsilon_0 \partial \mathbf{E} / \partial t$ in Eq. (1). From this identification we obtain Eq. (3).

Equation (3) can be applied to the polarization current $\partial \mathbf{P} / \partial t$, where $\mathbf{P}$ is a given polarization density. The replacement $\mathbf{J} \rightarrow \partial \mathbf{P} / \partial t$ in Eq. (3) and the fact that $\partial / \partial t$ can be taken

outside the retardation parentheses and even outside the integral leads to

$$\epsilon_0 \frac{\partial \mathbf{E}}{\partial t} = \frac{\partial}{\partial t} \left\{ -\frac{\mathbf{P}}{3} + \frac{1}{4\pi} \int d^3x' \left(\frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\mathbf{P}]) - [\mathbf{P}]}{R^3} + \frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{P}/\partial t]) - [\partial \mathbf{P}/\partial t]}{R^2 c} + \frac{\hat{\mathbf{R}} \times (\hat{\mathbf{R}} \times [\partial^2 \mathbf{P}/\partial t^2])}{R c^2} \right) \right\}, \quad (9)$$

which implies that the electric field produced by the polarization density is⁴

$$\mathbf{E} = -\frac{\mathbf{P}}{3\epsilon_0} + \frac{1}{4\pi\epsilon_0} \int d^3x' \left(\frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\mathbf{P}]) - [\mathbf{P}]}{R^3} + \frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{P}/\partial t]) - [\partial \mathbf{P}/\partial t]}{R^2 c} + \frac{\hat{\mathbf{R}} \times (\hat{\mathbf{R}} \times [\partial^2 \mathbf{P}/\partial t^2])}{R c^2} \right). \quad (10)$$

We can apply Eq. (10) to a point electric dipole possessing a time varying dipole moment $\mathbf{p}(t)$ located at the point $\mathbf{x}_0$. The polarization density for such a dipole is given by $\mathbf{P}(\mathbf{x}, t) = \mathbf{p}(t)\delta\{\mathbf{x} - \mathbf{x}_0\}$. After substituting this polarization density into Eq. (10) and integrating over all space, we find the Hertzian electric field:

$$\mathbf{E} = -\frac{\mathbf{p}(t)}{3\epsilon_0} \delta\{\mathbf{x} - \mathbf{x}_0\} + \frac{1}{4\pi\epsilon_0} \left(\frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\mathbf{p}]) - [\mathbf{p}]}{R^3} + \frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\dot{\mathbf{p}}]) - [\dot{\mathbf{p}}]}{R^2 c} + \frac{\hat{\mathbf{R}} \times (\hat{\mathbf{R}} \times [\ddot{\mathbf{p}}])}{R c^2} \right), \quad (11)$$

where $\hat{\mathbf{R}} = \mathbf{R}/R = (\mathbf{x} - \mathbf{x}_0)/|\mathbf{x} - \mathbf{x}_0|$, $\dot{\mathbf{p}} = \partial \mathbf{p}/\partial t$, and the square brackets $[\]$ now indicate that the enclosed quantity is to be evaluated at the retarded time $t' = t - |\mathbf{x} - \mathbf{x}_0|/c$. The electric field in Eq. (11) is usually presented without the delta function term.

The origin of the local term $\mathbf{J}/3$ in Eq. (3) might seem intriguing. However, if we use the Panofsky and Phillips formula for the retarded electric field:⁵

$$\mathbf{E} = \frac{1}{4\pi\epsilon_0} \int d^3x' \left(\frac{[\rho]\hat{\mathbf{R}}}{R^2} + \frac{2\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\mathbf{J}]) - [\mathbf{J}]}{R^2 c} + \frac{\hat{\mathbf{R}} \times (\hat{\mathbf{R}} \times [\partial \mathbf{J}/\partial t])}{R c^2} \right), \quad (12)$$

we can show the origin of the $\mathbf{J}/3$ term. Equation (12) is an equivalent expression of the generalized Coulomb law.³ The time derivative of Eq. (12) yields

$$\epsilon_0 \frac{\partial \mathbf{E}}{\partial t} = \frac{1}{4\pi} \int d^3x' \frac{[\partial \rho/\partial t]\hat{\mathbf{R}}}{R^2} + \frac{1}{4\pi} \int d^3x' \left(\frac{2\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{J}/\partial t]) - [\partial \mathbf{J}/\partial t]}{R^2 c} + \frac{\hat{\mathbf{R}} \times (\hat{\mathbf{R}} \times [\partial^2 \mathbf{J}/\partial t^2])}{R c^2} \right). \quad (13)$$

We use the continuity equation and write the first integral as (Appendix A)

$$\int d^3x' \frac{[\partial \rho/\partial t]\hat{\mathbf{R}}}{R^2} = -\frac{4\pi}{3} \mathbf{J} + \int d^3x' \left(\frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\mathbf{J}]) - [\mathbf{J}]}{R^3} + \frac{\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{J}/\partial t])}{R^2 c} \right). \quad (14)$$

The insertion of Eq. (14) into Eq. (13) gives Eq. (3) again.

The existence of the $\mathbf{J}/3$ term in Eq. (3) can be traced to the first term in Eq. (14). Thus, the origin of the $\mathbf{J}/3$ term is attributable to time variations of the charge density and ultimately to the continuity equation (charge conservation). I invite readers to decide which of the two derivations of Eq. (3) presented here they find more useful.

APPENDIX A: DERIVATION OF EQS. (6), (7), AND (14)

Consider the expansion

$$\nabla \times \left\{ \frac{[\mathbf{J}] \times \hat{\mathbf{R}}}{R^2} \right\} = -\nabla \times \left\{ [\mathbf{J}] \times \nabla \left(\frac{1}{R} \right) \right\} \quad (\text{A1a})$$

$$= -[\mathbf{J}] \nabla^2 \left(\frac{1}{R} \right) + \nabla \left(\frac{1}{R} \right) \nabla \cdot [\mathbf{J}] - \left(\nabla \left(\frac{1}{R} \right) \cdot \nabla \right) [\mathbf{J}] + \left([\mathbf{J}] \cdot \nabla \right) \nabla \left(\frac{1}{R} \right). \quad (\text{A1b})$$

It can be shown that⁶

$$\nabla^2 \left(\frac{1}{R} \right) = -4\pi \delta(\mathbf{x} - \mathbf{x}'), \quad (\text{A2a})$$

$$\nabla \cdot [\mathbf{J}] = -\frac{\hat{\mathbf{R}} \cdot [\partial \mathbf{J} / \partial t]}{c}, \quad (\text{A2b})$$

$$\left(\nabla \left(\frac{1}{R} \right) \cdot \nabla \right) [\mathbf{J}] = \frac{[\partial \mathbf{J} / \partial t]}{R^2 c}, \quad (\text{A2c})$$

$$\left([\mathbf{J}] \cdot \nabla \right) \nabla \left(\frac{1}{R} \right) = \frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\mathbf{J}]) - [\mathbf{J}]}{R^3} - \frac{4\pi}{3} [\mathbf{J}] \delta(\mathbf{x} - \mathbf{x}'). \quad (\text{A2d})$$

To obtain Eq. (A2d) we used the identity:⁷

$$\frac{\partial}{\partial x_i \partial x_j} \left(\frac{1}{R} \right) = \frac{3\hat{R}_i \hat{R}_j - \delta_{ij}}{R^3} - \frac{4\pi}{3} \delta_{ij} \delta(\mathbf{x} - \mathbf{x}'), \quad (\text{A3})$$

where $\hat{R}_i = R_i/R = (x_i - x'_i)/|x_i - x'_i|$ and δ_{ij} is the Kronecker delta symbol. The substitution of Eq. (A2) into Eq. (A1) leads directly to Eq. (6).

Consider the expansion

$$\begin{aligned} \nabla \times \left\{ \frac{[\partial \mathbf{J} / \partial t] \times \hat{\mathbf{R}}}{Rc} \right\} &= [\partial \mathbf{J} / \partial t] \nabla \cdot \left(\frac{\hat{\mathbf{R}}}{Rc} \right) - \left(\frac{\hat{\mathbf{R}}}{Rc} \right) \nabla \cdot [\partial \mathbf{J} / \partial t] \\ &\quad + \left(\frac{\hat{\mathbf{R}}}{Rc} \cdot \nabla \right) [\partial \mathbf{J} / \partial t] - \left([\partial \mathbf{J} / \partial t] \cdot \nabla \right) \frac{\hat{\mathbf{R}}}{Rc}. \end{aligned} \quad (\text{A4})$$

If we substitute the results

$$\nabla \cdot \left(\frac{\hat{\mathbf{R}}}{Rc} \right) = \frac{1}{R^2 c}, \quad (\text{A5a})$$

$$\nabla \cdot [\partial \mathbf{J} / \partial t] = -\frac{\hat{\mathbf{R}} \cdot [\partial^2 \mathbf{J} / \partial t^2]}{c}, \quad (\text{A5b})$$

$$\left(\frac{\hat{\mathbf{R}}}{Rc} \cdot \nabla \right) [\partial \mathbf{J} / \partial t] = -\frac{[\partial^2 \mathbf{J} / \partial t^2]}{Rc^2}, \quad (\text{A5c})$$

$$\left([\partial \mathbf{J} / \partial t] \cdot \nabla \right) \frac{\hat{\mathbf{R}}}{Rc} = -\frac{2\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{J} / \partial t]) - [\partial \mathbf{J} / \partial t]}{R^2 c}, \quad (\text{A5d})$$

into Eq. (A4), we obtain Eq. (7).

The proof of Eq. (14) goes as follows: If the continuity equation and Eq. (A2b) are substituted into the identity $[\nabla' \cdot \mathbf{J}] = \nabla' \cdot [\mathbf{J}] + \nabla \cdot [\mathbf{J}]$ and the resulting equation multiplied by $\hat{\mathbf{R}}/R^2$, we obtain

$$\frac{[\partial \rho / \partial t] \hat{\mathbf{R}}}{R^2} = -\frac{(\nabla' \cdot [\mathbf{J}]) \hat{\mathbf{R}}}{R^2} + \frac{\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{J} / \partial t])}{R^2 c}, \quad (\text{A6})$$

and hence

$$\int d^3 x' \frac{[\partial \rho / \partial t] \hat{\mathbf{R}}}{R^2} = -\int d^3 x' \frac{(\nabla' \cdot [\mathbf{J}]) \hat{\mathbf{R}}}{R^2} + \int d^3 x' \frac{\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\partial \mathbf{J} / \partial t])}{R^2 c}. \quad (\text{A7})$$

The integral involving $\nabla' \cdot [\mathbf{J}]$ can be transformed further by examining the components of the integrand

$$-\frac{(\nabla' \cdot [\mathbf{J}]) \hat{\mathbf{R}}^i}{R^2} = -\frac{\partial}{\partial x'_k} \left\{ [\mathbf{J}]_k \frac{\partial}{\partial x'_i} \left(\frac{1}{R} \right) \right\} + \frac{3\hat{\mathbf{R}}^i(\hat{\mathbf{R}} \cdot [\mathbf{J}]) - [\mathbf{J}]^i}{R^3} - \frac{4\pi}{3} [\mathbf{J}]^i \delta(\mathbf{x} - \mathbf{x}'), \quad (\text{A8})$$

where Eq. (A3) has been used and summation over the index k is implied. The volume integral of the first term of Eq. (A8) can be transformed into a surface integral with the aid of Gauss' theorem, and hence vanishes assuming that the currents are localized:

$$\int d^3 x' \frac{\partial}{\partial x'_k} \left\{ [\mathbf{J}]_k \frac{\partial}{\partial x'_i} \left(\frac{1}{R} \right) \right\} = \oint d\mathbf{S}' \cdot \left\{ [\mathbf{J}] \frac{\partial}{\partial x'_i} \left(\frac{1}{R} \right) \right\} = 0. \quad (\text{A9})$$

The volume integral of the last term in Eq. (A8) gives $-(4\pi/3)\mathbf{J}$. Therefore,

$$-\int d^3 x' \frac{(\nabla' \cdot [\mathbf{J}]) \hat{\mathbf{R}}}{R^2} = -\frac{4\pi}{3} \mathbf{J} + \int d^3 x' \left(\frac{3\hat{\mathbf{R}}(\hat{\mathbf{R}} \cdot [\mathbf{J}]) - [\mathbf{J}]}{R^3} \right). \quad (\text{A10})$$

From Eqs. (A7) and (A10) we obtain Eq. (14).

ACKNOWLEDGMENTS

The author thanks David J. Griffiths and Mark A. Heald for useful comments. The support of FICSAC is gratefully acknowledged.

* Electronic address: herasgomez@gmail.com

¹ D. J. Griffiths and M. A. Heald, “Time-dependent generalizations of the Biot-Savart and Coulomb Laws,” *Am. J. Phys.* **59**, 111–117 (1991).

² The non-self-referential form of Eq. (2) (obtained by substituting Eq. (3) into Eq. (2)) implies complicated integrations (it is defined as an integral over all space, the integrand of which is itself a series of integrals over all space) and therefore it is not generally useful in practice.

³ O. D. Jefimenko, *Electricity and Magnetism* (Electret Scientific Co., Star City, WV, 1989), 2nd ed., p. 516; J. D. Jackson, *Classical Electrodynamics* (John Wiley & Sons, New York, 1999), 3rd ed., Sec. 6.5.

⁴ J. A. Heras, “Unified model based on U(1) duality symmetry of polarization and magnetization,” *Phys. Rev. E* **58**, R6951–R6954 (1998). Equation (9) implies Eq. (10) with an additive integration term $\mathbf{E}_0(\mathbf{x})$. Because Eq. (10) satisfies a wave equation, the term $\mathbf{E}_0(\mathbf{x})$ is ultimately a solution of the Laplace equation. This additive term is shown to vanish under the usual assumption that the electric field vanishes at infinity.

⁵ W. K. H. Panofsky and M. Phillips, *Classical Electricity and Magnetism*, (Addison-Wesley, Reading, MA, 1962) 2nd ed. See also K. T. McDonald, “The relation between expressions for time-dependent electromagnetic fields given by Jefimenko and by Panofsky and Phillips,” *Am. J. Phys.* **65**, 1074–1076 (1997) and J. A. Heras, “New approach to the classical radiation fields of moving dipoles,” *Phys. Lett. A* **237**, 343–348 (1998).

⁶ The reader can find an approach for deriving identities involving retarded quantities in J. A. Heras, “Can Maxwell’s equations be obtained from the continuity equation?” *Am. J. Phys.* **75**, 652–657 (2007).

⁷ C. P. Frahm, “Some novel delta-function identities,” *Am. J. Phys.* **51**, 826–829 (1983).